



Wall Mounting Guide

Wall Mountable Switches

1.1 Wall Mounting Preparation

Before mounting the switch, you need to prepare the tools below:

- A screw driver.
- Two screws which complies to the corresponding standard. For details, see [Wall Mounting Specification](#).

1.2 Wall Mounting Procedure

On the bottom of the panel, there are two mounting holes. You need to drive two screws into the wall, then mount the switch on the wall. Note that the switch should be mounted on the wall upright rather than sideways. For TL-SF1008P/TL-SF1008LP/TL-SF1009P/TL-SG1008P, the switch should be mounted with the ports facing downward and the LEDs facing upward.

- 1) Determine the location on the wall where you want to mount the switch.
- 2) Mark the wall where the two mounting holes are. The distance between the two marks must be the same as that between the two mounting holes of the switch. For the wall-mounting-holes distance, see [Wall Mounting Specification](#).
- 3) Drive the screws into the wall at the marks using the screw driver. For the Screw-Head-to-Wall Minimum Distance, see [Wall Mounting Specification](#).
- 4) Mount the switch on the wall.

1.3 Wall Mounting Specification

Model	Screw Standard of ANSI B1.1	Minimum Length of Screw	Screw-Head-to-Wall Minimum Distance	Wall-Mounting-Holes Distance
LS105G	4#, (5#), 6#	7mm	1.5mm	76mm
LS108G	4#, (5#), 6#	7mm	1.5mm	65mm
LS1005G	4#, (5#), 6#	7mm	1.5mm	38mm
LS1008G	4#, (5#), 6#	7mm	1.5mm	48mm
TL-SF1005LP	4#, (5#), 6#, 8#	8.5mm	1.5mm	39mm
TL-SF1005P	4#, (5#), 6#, 8#	8.5mm	1.5mm	39mm
TL-SF1006P	4#, (5#), 6#, 8#	8.5mm	1.5mm	94mm
TL-SF1008LP	4#, (5#), 6#, 8#	8.5mm	1.5mm	105mm
TL-SF1008P	4#, (5#), 6#, 8#	8.5mm	1.5mm	105mm
TL-SF1009P	4#, (5#), 6#, 8#	8.5mm	1.5mm	105mm
TL-SF1016D	4#, (5#), 6#	8.5mm	1.5mm	157.2mm
TL-SG1005LP	4#, (5#), 6#, 8#	8.5mm	1.5mm	39mm

Model	Screw Standard of ANSI B1.1	Minimum Length of Screw	Screw-Head-to-Wall Minimum Distance	Wall-Mounting-Holes Distance
TL-SG1005P	4#, (5#), 6#, 8#	8.5mm	1.5mm	39mm
TL-SG1008D	4#	8mm	2mm	100mm
TL-SG1008P	4#, (5#), 6#, 8#	8.5mm	1.5mm	105mm
TL-SG105	4#, (5#), 6#	7mm	1.5mm	39mm
TL-SG105E	4#, (5#), 6#	7mm	1.5mm	52mm
TL-SG105-M2	4#, (5#), 6#	7mm	1.5mm	150mm
TL-SG105PE	4#, (5#), 6#	7mm	1.5mm	39mm
TL-SG105S	4#, (5#), 6#	7mm	1.5mm	39mm
TL-SG108	4#, (5#), 6#, 8#	8.5mm	1.5mm	94mm
TL-SG108E	4#, (5#), 6#	7mm	1.5mm	110mm
TL-SG108-M2	4#, (5#), 6#	7mm	1.5mm	150mm
TL-SG108PE	4#, (5#), 6#, 8#	8.5mm	1.5mm	94mm
TL-SG108S	4#, (5#), 6#	7mm	1.5mm	94mm
TL-SG116	4#, 6#	8.5mm	1.5mm	200mm
TL-SG116E	4#, 6#	8.5mm	1.5mm	200mm
TL-SG1210MP	4#, (5#), 6#, 8#	8.5mm	1.5mm	150mm
TL-SG1210MPE	4#, (5#), 6#, 8#	8.5mm	1.5mm	150mm
TL-SG1210P	4#, (5#), 6#, 8#	7mm	1.5mm	150mm
TL-SG2008	4#, (5#), 6#	7mm	1.5mm	150mm
TL-SG2008P	4#, (5#), 6#	7mm	1.5mm	150mm
TL-SG2210P	4#, (5#), 6#	7mm	1.5mm	150mm
TL-SL1210MP	4#, (5#), 6#, 8#	7mm	1.5mm	150mm
TL-SL1311MP	4#, (5#), 6#, 8#	8.5mm	1.5mm	150mm
TL-SX105	4#, (5#), 6#	7mm	1.5mm	150mm