



## 4-Port Dual-Monitor HDMI KVM Switch

HDMI Dual-Display Connections, 4K@30Hz, USB Connections, 3.5 mm Audio and Mic Connections, USB 2.0 Hub, Black

Part No.: [153539](#)

EAN-13: 0766623153539 | UPC: 766623153539

---

### HDMI Dual Monitor KVM Switch with 4 ports - Easy access and control in 4K UHD

The Manhattan 4-Port Dual-Monitor HDMI KVM Switch is a compact solution for providing access and control over four HDMI/USB-equipped computers from a single keyboard and mouse and up to two monitors. It helps save you time on installation with its included combo cables — there's no need to purchase additional ones — that easily connect directly to the system.

#### Easy to use for improved efficiency

This KVM Switch helps you access your systems more efficiently without the expense and clutter of extra keyboards, mice, and monitors. You select your connected computers and audio/mic channels through the front-panel push-buttons or keyboard hotkeys. The enhanced control this KVM switch provides is ideal for high graphical content in applications like video editing, digital signage server control, medical imaging, multimedia design or dual system control workstations. It is also great for sharing four multimedia PCs or notebooks with a single HDMI TV.

#### 4K resolution at 30 Hz and full audio support

The ever-growing demand for higher video quality and the evolution of HDMI technology has put 4K-enabled computers and displays in many visually ambitious workplace and commercial applications. Supporting up to 3840 x 2160 (4K) resolution at 30 Hz, this KVM Switch is right at home in your Ultra-High-Definition-equipped setup. You can connect a second monitor to enjoy maximized viewing. You also get full audio compatibility, with support for digital

audio and separate analog 3.5 mm stereo audio jacks for microphones and speakers or headphones.

## **Additional USB hub port**

The integrated USB 2.0 hub offers a front-facing USB-A port in addition to keyboard and mouse ports. This hub port works among your attached computers as if it were directly connected to your host computer so you can avoid having to constantly plug/unplug devices such as printers, storage drives or scanners.

## **Compatible with Windows<sup>®</sup>, Mac<sup>®</sup>, Linux<sup>®</sup> and more**

Being OS independent, this HDMI KVM switch not only supports Windows, Mac OS and Linux, but it is also compatible with Unix<sup>®</sup> and even Novell<sup>®</sup> NetWare to fully support older legacy hardware.

### **Features:**

- Controls four HDMI and USB-A equipped computers from a single keyboard and mouse and up to two monitors
- Full stereo audio support through 3.5 mm speaker and microphone connections
- Switching via front-panel push buttons or keyboard hot keys
- Resolutions up to Ultra-High-Definition (UHD) 4K@30Hz (3840 × 2160)
- Additional USB 2.0 type-A hub port to connect storage drives, printers, scanners and more
- Digital audio support through HDMI with Dolby True HD and DTS HD Master Audio
- Ideal for sharing multiple multimedia PCs or notebooks with a single HDMI TV
- Supports Windows<sup>®</sup>, Mac OS<sup>®</sup>, Linux<sup>®</sup>, Unix<sup>®</sup> and Novell<sup>®</sup>
- True Transparent USB (TTU) emulation technology supports most keyboard and mouse designs
- HDCP 1.4 compliant
- BIOS-level hardware installation; no drivers or control software required
- Four 1.8 m (6 ft.) HDMI/USB-B/Audio to USB-A combo connection cables included
- Compact desktop format with rugged metal housing
- USB powered; use optional 9 V / 300 mA power supply (not included) if your setup delivers insufficient power input
- Three-year warranty

## Specifications:

### Standards and Certifications

- CE
- RoHS
- FCC

### Connections

- Console ports
  - 2 x HDMI female 19-pin
  - 2 x USB-A female 4-pin
  - 1 x 3.5 stereo audio microphone female
  - 1 x 3.5 stereo audio speaker female
- Computer/host ports
  - 8 x HDMI female 19-pin
  - 4 x USB-B female 4-pin
  - 4 x 3.5 stereo audio microphone/speaker female combo port
- Other
  - 1 x USB-A female 9-pin
  - 1 x 9.0 V DC/0.3 A power jack

### LEDs

- 4 x red (online)
- 4 x green (selected)

### Supported Operating Systems

- Windows 2000/2003/XP/Vista/7/8/8.1/10
- Apple Mac OS 9.0 to 10.6 (Snow Leopard)
- Linux RedHat 9.0 or higher/SuSe 10 or higher/Debian 3.1/4.0/Ubuntu 7.04/7.10
- UNIX AIX 4.3 or higher/FreeBSD 5.5 or higher/Sun Solaris 8 or higher
- Novell Netware 6.0 or higher

### Physical

- Dimensions (L x W x H): 202 x 110 x 66 mm (7.95 x 4.33 x 2.6 in.)
- Weight: 850 g (1.87 lbs.)
- Housing: metal

### Operating Environment

- Operation temperature: 0 - 50°C (32 - 122°F)
- Storage temperature: -20 - 60°C (-4 - 140°F)
- Humidity (noncondensing): 0 - 80%

### Package Contents

- 4-Port Dual-Monitor HDMI KVM Switch
- Four 1.8 m (6 ft.) HDMI/USB-B/Audio to USB-A combo cables included

Please note: Mac® computers can only be controlled with a standard PC mouse and keyboard, not with Mac peripherals.

