



Statement of Volatility – Dell Latitude 3520

⚠ CAUTION: A CAUTION indicates either potential damage to hardware or loss of data and tells you how to avoid the problem.

The Dell Latitude 3520 contains both volatile and non-volatile components. Volatile components lose their data immediately after power is removed from the component. Non-volatile components continue to retain their data even after power is removed from the component. The following Non-volatile components are present on the Latitude 3520 system board.

Table 1. List of Non-Volatile Components on System Board

| Description | Reference Designator | Volatility Description | User Accessible for external data | Remedial Action (Action necessary to prevent loss of data) |
|---|---|--|-----------------------------------|--|
| SSD drive(s) | SSD1 | Non-Volatile magnetic media, various sizes in GB. SSD (solid state flash drive). | Yes | Low level format |
| Hard drive(s) | HDD1 | Non-Volatile magnetic media, various sizes in GB | Yes | Low level format |
| System BIOS/EC | U2504 (32 MB) | Non-Volatile memory, 32MB, System BIOS and Video BIOS for basic boot operation, PSA (on board diags), Intel ME firmware for system configure, security and protection and ISH firmware. | No | NA |
| Thunderbolt EEPROM | U7103 | Non-Volatile memory, 8 Mbit (1 MB) (Thunderbolt FW) | No | NA |
| USB-Type C PD | U7202 | Non-Volatile memory for USB type-C PD F/W | No | NA |
| LCD Panel EEDID EEPROM | Part of panel assembly | Non-Volatile memory, Stores panel manufacturing information, display configuration data | No | NA |
| System Memory – DDR4 memory | Two DIMM on board DDR4 memory: DM1/DM2 | Volatile memory in OFF state (see state definitions later in text) Four packages memories must be populated. System memory size will depend on the size of each piece memory and must be between 4GB and 32 GB. | Yes | Power off system |
| RTC CMOS | RTC1 | Non-Volatile memory 256 bytes Stores CMOS information | No | NA |
| Video memory – frame buffer | VRAM1, VRAM2 | Volatile memory in off state. UMA uses main system memory size allocated out of main memory. | No | Power off system |
| Embedded Flash in embedded controller MEC1515 | U2401 | 256 KB of embedded Flash memory for keyboard controller BIOS code, asset tag and BIOS passwords | No | N/A |
| TPM Controller | U9101 | Non-Volatile memory, 220.8K bits (27.6K bytes) ROM | No | N/A |

| Description | Reference Designator | Volatility Description | User Accessible for external data | Remedial Action (Action necessary to prevent loss of data) |
|-----------------------------|----------------------|---|-----------------------------------|--|
| Touch screen Embedded Flash | N/A | Non-Volatile memory | No | N/A |
| Digital IMVP9 controller | PU4601 | Non-Volatile memory, 4096 bit (512 B) Digital IMVP9 controller | No | N/A |

△ CAUTION: All other components on the system board lose data if power is removed from the system. Primary power loss (unplugging the power cord and removing the battery) destroys all user data on the memory (DDR4, 2667 MHz). Secondary power loss (removing the on-board coin-cell battery) destroys system data on the system configuration and time-of-day information.

Copyright © 2021 Dell Inc. or its subsidiaries. All rights reserved. Dell, EMC, and other trademarks are trademarks of Dell Inc. or its subsidiaries. Other trademarks may be trademarks of their respective owners.