

## 4-Port 4K 60Hz DisplayPort KVM Switch - USB 5Gbps Hub

### Product IDs

P4AD122-KVM-SWITCH

### Product Information

For the latest software, manuals, product information, technical specifications, and declarations of conformance, please visit:

[www.StarTech.com/P4AD122-KVM-SWITCH](http://www.StarTech.com/P4AD122-KVM-SWITCH)

### Hotkey Commands

Hotkey commands are keystroke sequences that initiate computer/device functions. Hotkey commands can be used to initiate KVM Switch functions. A hotkey command sequence must be initiated by the HK\_LCode, followed by 1-2 additional keystrokes. Successful hotkey command inputs result in a high-pitched beep. Unsuccessful hotkey command inputs result in a low-pitched beep.

#### Notes:

- All keystroke combinations must be entered in rapid succession.
- Press and release the indicated keys, unless otherwise specified.
- Numbers entered during the hotkey sequence cannot be entered using a number pad

#### HK\_LCode

##### Option 1

- Scr Lck + Scr Lck

##### Option 2

- Left Ctrl + Left Ctrl

##### Option 3

- Left Shift (Hold) + Num Lck + Num Lck + Release Left Shift

Hotkey Command	Function
<b>HK_LCode + 1 ~ 4</b>	<ul style="list-style-type: none"> <li>• Select PC 1 ~ PC 4</li> </ul>
<b>HK_LCode + F1</b> or Press <b>Port Selection Buttons 3 &amp; 4</b>	<ul style="list-style-type: none"> <li>• Start Auto Scan</li> </ul>
<b>HK_LCode + F2</b>	<ul style="list-style-type: none"> <li>• Start Manual Scan -- Manually switch back and forth between PCs</li> <li>• Press the <b>Up Arrow</b> or <b>Down Arrow</b> key to select the next/previous PC</li> </ul>
<b>HK_LCode + F3</b> or Press <b>Port Selection Buttons 1 &amp; 2</b>	<ul style="list-style-type: none"> <li>• Adjust Scan Rate -- KVM Switch generates one to four beeps that indicate the duration of the scan time:               <ul style="list-style-type: none"> <li>• One beep = 3 seconds</li> <li>• Two beeps = 8 seconds</li> <li>• Three beeps = 15 seconds</li> <li>• Four beeps = 30 seconds</li> </ul> </li> </ul>
<b>HK_LCode + F5</b>	<ul style="list-style-type: none"> <li>• Enable/Disable the binding of PC and Audio Switching.</li> <li>• Bound by default forcing PC and Audio to switch together               <ul style="list-style-type: none"> <li>• <b>Unbound</b> = PC Audio stops following the selected PC when switching (1 beep)</li> <li>• <b>Bound</b> = PC Audio matches the selected PC (2 beeps)</li> </ul> </li> </ul>
<b>HK_LCode + A</b>	<ul style="list-style-type: none"> <li>• Force Audio to follow selected PC               <ul style="list-style-type: none"> <li>• If audio was unbound, this command will rebind audio to switch with the PC ports</li> </ul> </li> </ul>
<b>Left Shift (Hold) + Num Lck + Num Lck + Release Shift + Left Ctrl</b>	<ul style="list-style-type: none"> <li>• Enable or disable hotkey functionality</li> <li>• Enabled by default</li> </ul>