

| | | |
|-----------------------------|---|--------------------|
| Overview | Model | RV-L11-A |
| Cleaner | Navigation | Laser |
| | Cleaning Router | Planning |
| | Suction Power | Up to 3000Pa |
| | Duration | 110min |
| | Battery | 3200mAh |
| | Charging Time | 4h |
| | Working Noise | 65dB |
| | Height of Obstacle Crossing | 2cm |
| | Dust Bin Capacity | 300ml |
| | Water Tank Capacity | 250ml |
| | Water Tank Type | Electrical Control |
| | Carpet Boost | Support |
| | No-go Area Setting | Support |
| | Virtual Wall | Support |
| | Scheduled Cleaning | Support |
| | Auto Returning to Charge | Support |
| | Dimension | 350*350*98mm |
| Working Environment | Temperature: 0-40°C Humidity: ≤90% | |
| Dirt Disposal Charging Dock | Suction Power | 26KPa |
| | Working Noise | <80dB(A) |
| | Power Input | AC 220V 5A |
| | Power Output | DC 24V 1.5A |
| | Dimension | 356*250*193mm |