

# Wireless shipping and barcode label printer

QL-1110NWB



CONTINUOUS  
ROLL



PRE-SIZED  
LABELS



BLUETOOTH  
CONNECTION



NETWORK  
CONNECTION



PC  
CONNECTION

[brother.co.uk/QL1110NWB](http://brother.co.uk/QL1110NWB)



# QL-1110NWB

## Wireless shipping and barcode label printer



The Brother QL-1110NWB is a high-speed label printer engineered with flexible connectivity options – Bluetooth, wired and wireless interfaces.

This business-quality label printer lets you create cost-effective adhesive paper labels, up to 4" wide, for packages, envelopes, postage and more.

The unique to Brother feature of automatic crop print function enables online sellers to easily print product and other barcode labels instead of using A4/letter size label sheet templates\*. The barcode labels comply with Fulfilled by Amazon requirements.

The Brother QL-1110NWB delivers fast print speeds of up to 69 standard address labels per minute with black text at 300dpi. USB Host interface offers additional functionality.

Auto cutter allows for printing one or multiple labels at a time, eliminating wasted label sheets.



The QL-1110NWB supports Apple AirPrint to enable printing from compatible apps on iOS devices and Mac.

## QL-1110NWB

### Included items

In the box

Printer  
DK-11247 - Large shipping pre-sized labels (41 labels)  
DK-22205 - 62mm width continuous roll (8.1 metres)  
USB cable  
AC power cord  
Documentation

### Printing / Media

Printing technology	Direct thermal
Print resolution	300 x 300dpi
Maximum print speed*	69 standard address labels per minute or 110mm per second*
Label widths	12mm - 103.6mm
Maximum print width	101.6mm
Minimum label length	25.4mm
Maximum label length	3 metres (Windows / MacOS)   1 metre (P-touch Editor Lite / iPrint&Label)**
Media sensor type	Reflective
Cutter	Yes (full cut / guillotine type)
Media types	DK rolls (DK pre-sized labels / DK continuous tape)

### Control panel

Buttons	Power / Feed / Cut / P-touch Editor Lite
---------	--

### Connectivity

USB	USB version 2.0 full-speed (type B)
USB host capability	Yes (HID class)
Bluetooth	Bluetooth 2.1+EDR
Bluetooth profiles	SPP (Serial Port Profile) OPP (Object Push Profile) BIP (Basic Imaging Profile) HCRP (Hard Copy Cable Replacement Profile)
iOS and Android compatibility	Yes (including MFi and AirPrint)

### Memory

Flash (for label templates)	7.8MB
Locations (for label templates)	255

### Power

Power	220-240V AC internal power supply
Energy Star Certification	Yes

### Weights/Dimensions

Dimensions	170(w) x 222(h) x 151(d) mm
Weight	1.73kg

### Software / Firmware

Operating system support (visit <a href="http://support.brother.com">http://support.brother.com</a> for latest downloads and support)	Microsoft® Windows® 7 / Windows® 8 / Windows® 8.1 / Windows® 10 Microsoft® Windows Server® 2008/2008 R2 / 2012 / 2012 R2 / 2016 macOS v10.11/10.12/10.13 iOS 10/11 (iPrint&Label App) iOS 7/8/9/10/11 (iOS SDK) Android 4.4 or greater (iPrint&Label App) Android 4.4 or greater (Android SDK)
--	---

## QL-1110NWB

Software / Firmware	
Label editor support	P-touch Editor (Windows/Mac) Add-In for Microsoft Word/Excel/Outlook iPrint&Label (iOS/Android)
SDK availability (visit <a href="http://www.brother.eu/developer">http://www.brother.eu/developer</a> )	b-PAC (for Windows) iOS SDK Android SDK
Supported printer commands	ZPLII emulation (upon request) ESC/P P-touch template Raster
Template update by FTP transfer	Yes
Label crop and print (convert A4 sheets of labels to individual labels automatically)	Yes (Windows only)
Barcode symbologies (using P-touch Editor for Windows)	CODE39, CODE128, UCC/EAN128(GS1-128), ITF(I-2/5), CODABAR(NW-7), UPC-A, UPC-E, EAN13, EAN8, ISBN-2(EAN13 AddOn2), ISBN-5(EAN13 AddOn5), Laser Barcode, POSTNET, RSS(RSS14 Standard, RSS14 Truncated, RSS14 Stacked, RSS14 Stacked Omni, RSS Limited, RSS Expanded, RSS Expanded Stacked), AztecCode, PDF417(Standard, Truncate, Micro), QR code(Model1, Model2, Micro), Data Matrix(ECC Square, ECC Rectangular), MaxiCode(Model2, Model3, Model4, Model5), IMB
Barcode symbologies (using P-touch Editor for Mac)	CODE39, CODE128, UCC/EAN128(GS1-128), ITF(I-2/5), CODABAR(NW-7), UPC-A, UPC-E, EAN13, EAN8, ISBN-2(EAN13 AddOn2), ISBN-5(EAN13 AddOn5), Laser Barcode, POSTNET, RSS(RSS14 Standard, RSS14 Truncated, RSS14 Stacked, RSS14 Stacked Omni, RSS Limited, RSS Expanded, RSS Expanded Stacked), PDF417(Standard, Truncate, Micro), QR code(Model1, Model2, Micro), Data Matrix-(ECC Square, ECC Rectangular), MaxiCode(Model2, Model3, Model4, Model5), IMB
Barcode symbologies (Built-in printer firmware)	CODE39, CODE128, UCC/EAN-128(GS1-128), ITF(I-2/5), CODABAR(NW-7), UPC-A, UPC-E, EAN13 (JAN13), EAN8, GS1 DataBar(RSS)(GS1 DataBar Omnidirectional,GS1 DataBar Truncated,GS1 DataBar Stacked,GS1 DataBar Stacked Omnidirectional,GS1 DataBar Limited,GS1 DataBar Expanded,GS1 DataBar Expanded Stacked), PDF417(Standard, Truncate, Micro), QR Code(Model 1, Model 2, Micro), Data Matrix (ECC200 Square, ECC200 Rectangular), MaxiCode, CODE93, POSTNET, UPC-E EXTENTION, MSI, Aztec
Internal fonts	Bitmap fonts: Helsinki, Brussels, Letter Gothic Bold, San Diego, Brougham. Bitmap font sizes: 24 dots, 32 dots, 48 dots. Outline fonts: Helsinki, Brussels, Letter Gothic. Outline font sizes: 33 dots - 400 dots (22 sizes)

\* Brother standard test environment. Using DK-11201 standard address labels and USB connection.

\*\* Using USB connection through P-touch Editor.