

## 2U Vented Center-Mount Shelf - 14/20 in. Depth

### Product IDs

SHELF-2U-14-CENTER-V  
SHELF-2U-20-CENTER-V

### Product Diagram

Front - Angled View



\*Product may vary from image

Component	Function
1 Shelf Lip	• Mount the <b>2U Vented Center-Mount Shelf</b> with the <b>Shelf Lip</b> oriented upwards to prevent <b>Equipment</b> from slipping o
2 Mounting Holes (x 8)	• Mount the <b>2U Vented Center-Mount Shelf</b> into a <b>Rack</b> .

### Product Information

For the latest manuals, product information, technical specifications, and declarations of conformance, please visit:

[www.StarTech.com/SHELF-2U-14-CENTER-V](http://www.StarTech.com/SHELF-2U-14-CENTER-V)  
[www.StarTech.com/SHELF-2U-20-CENTER-V](http://www.StarTech.com/SHELF-2U-20-CENTER-V)

### Requirements

- 2U Available Rack Space
- Phillips Head Screwdriver
- (Optional) Cage Nut Tool

### Warnings

- Read the entire manual and ensure the instructions are fully understood before assembling and/or using this product.
- Before adding equipment to this product, ensure this product has been properly mounted.
- Ensure the weight of the equipment does not exceed the weight capacity of this product. If the weight capacity is exceeded, personal injury or damage to the equipment are possibilities. This product can support the following weight: up to 200.6 lb. (91 kg). This product can only support the maximum weight capacity if 8 M6 Screws / Cage Nuts / Plastic Washers are used to a x this product to a rack.

### Package Contents

- 2U Vented Center-Mount Shelf x 1
- M6 Cage Nuts x 10
- M6 Screws x 10
- M6 Plastic Washers x 10
- Quick-Start Guide x 1

### Installation

Mount the 2U Vented Center-Mount Shelf into a Rack

Use the included **M6 Cage Nuts**, **M6 Screws**, and **M6 Plastic Washers** to install the **2U Vented Center-Mount Shelf**.

**Notes:** This product can support the following weight: 200.6 lb. (91 kg).

The following installation instructions are for square mounting holes.

1. Locate a suitable location in a **Rack** to mount the **2U Vented Center-Mount Shelf**.  
  
**Note:** The **2U Vented Center-Mount Shelf** itself requires **2U** of space within a **Rack**.
2. Insert the **Wing** (side) of an **M6 Cage Nut** into the back of the a **Cage Nut Hole**.
3. Insert the second **Wing** of the **M6 Cage Nut** into the selected **Cage Nut Hole**, using pressure by hand, or with a **Cage Nut Tool**.
4. Repeat steps 2 and 3 to insert a total of 8 **Cage Nuts**.
5. Thread an **M6 Plastic Washer** over an **M6 Screw**. Repeat until 8 **M6 Screw Assemblies** have been prepared.

6. Align the **Mounting Holes** in the **2U Vented Center-Mount Shelf** with the **M6 Cage Nuts** installed in steps 2-4.
7. Insert the **M6 Screw Assemblies** through the **Mounting Holes** in the **2U Vented Center-Mount Shelf** and into the **M6 Cage Nuts** and tighten, using a **Phillips Head Screwdriver**.

## Regulatory Compliance

### Use of Trademarks, Registered Trademarks, and other Protected Names and Symbols

This manual may make reference to trademarks, registered trademarks, and other protected names and/or symbols of third-party companies not related in any way to StarTech.com. Where they occur these references are for illustrative purposes only and do not represent an endorsement of a product or service by StarTech.com, or an endorsement of the product(s) to which this manual applies by the third-party company in question. StarTech.com hereby acknowledges that all trademarks, registered trademarks, service marks, and other protected names and/or symbols contained in this manual and related documents are the property of their respective holders.

PHILLIPS® is a registered trademark of Phillips Screw Company in the United States or other countries.

## Warranty Information

This product is backed by a lifetime warranty.

For further information on product warranty terms and conditions, please refer to [www.startech.com/warranty](http://www.startech.com/warranty).

## Limitation of Liability

In no event shall the liability of StarTech.com Ltd. and StarTech.com USA LLP (or their officers, directors, employees or agents) for any damages (whether direct or indirect, special, punitive, incidental, consequential, or otherwise), loss of profits, loss of business, or any pecuniary loss, arising out of or related to the use of the product exceed the actual price paid for the product. Some states do not allow the exclusion or limitation of incidental or consequential damages. If such laws apply, the limitations or exclusions contained in this statement may not apply to you.

### StarTech.com Ltd.

45 Artisans Crescent  
London, Ontario  
N5V 5E9  
Canada

### StarTech.com LLP

4490 South Hamilton  
Road  
Groveport, Ohio  
43125  
U.S.A.

### StarTech.com Ltd.

Unit B, Pinnacle 15  
Gowerton Road  
Brackmills,  
Northampton  
NN4 7BW  
United Kingdom

### StarTech.com Ltd.

Siriusdreef 17-27  
2132 WT Hoofddorp  
The Netherlands

FR: [startech.com/fr](http://startech.com/fr)  
DE: [startech.com/de](http://startech.com/de)  
ES: [startech.com/es](http://startech.com/es)  
NL: [startech.com/nl](http://startech.com/nl)  
IT: [startech.com/it](http://startech.com/it)  
JP: [startech.com/jp](http://startech.com/jp)