



SPECIFICATIONS

Product Name	MAG PANO M100R PZ / WHITE
Case Form Factor	Micro- ATX Tower
Motherboard Form Factor Support	M-ATX(Back-connect supported) / ITX
I/O Ports	1 x USB 3.2 Gen 1 Type-A 1 x USB 3.2 Gen 2x2 Type-C 1 x Audio-Out / Mic-in 1 x LED Switch Button 1 x Power Button
Drive Mount Support	1 x 2.5" 1 x 2.5"/3.5" combo (up to 2 x 2.5" or 1 x 2.5" + 1 x 3.5")
Expansion Slots	5
Maximum GPU Length	390 mm / 15.35 inches *Support horizontal installation only.
Maximum CPU Cooler Height	175 mm / 6.9 inches
Power Supply Support	ATX
Maximum PSU Length	200 mm / 7.87 inches
Fan Size Support	Top: 3 x 120 mm / 2 x 140 mm Front: NA Rear: 1 x 120 mm / 1 x 140 mm Side: 3 x 120 mm Bottom: 1 x 120 mm PSU Shroud: 2 x 120 mm
Pre-installed Fan Size	Side: 3 x 120 mm Rear: 1 x 120 mm
Pre-installed Fan Type	Side: 3 x ARGB Fan (Reverse-blade) Rear: 1 x ARGB Fan
Radiator Size Support	Top: 120 / 240 / 360 mm Front: NA Rear: 120 / 140 mm Side: NA Bottom: NA
Dimensions (DxWxH)	440 x 235 x 405 mm / 17.32 x 9.25 x 15.94 inches
Net Weight	8.66 kg
Gross Weight	11.29 kg

FEATURES



Pre-build with Reverse-blade Fan

Pre-installed on the side are reverse blade fans, allowing the unobstructed display of the ARGB fan's beauty without any interference from fan frames.



Support Back-Connect Motherboard

Supporting back-connect motherboards enables easy installation without the worry of forgetting to connect cables, which might otherwise require disassembling graphics cards and coolers.



270-degree Panoramic Display

Drawing inspiration from the MAG logo, create a distinctive chassis design that embodies the unique MAG characteristics. The front interior of the chassis incorporates a space for displaying figurines, complemented by a 270-degree panoramic tempered glass, transforming it into a showcase-style chassis.



GPU Support Stand


Equipped with a level indicator to ensure effortless adjustment of the support height during installation, preventing sagging. Meanwhile, its magnetic base secures more stability within the chassis.



1 to 4 ARGB-FAN Control Board

This fan control board supports up to 4 x ARGB fan function. Allow you to use the LED switch button to adjust the ARGB lighting intuitively.

CONNECTIONS



1. 1x USB 3.2 Gen 2x2 Type-C
2. 1x USB 3.2 Gen 1 Type-A
3. Mic In/ Audio Out
4. LED Switch Button
5. Power Button