





# **EVOLVE 65** TE

Technology for life's new rhythm

© 2024 GN Hearing A/S (GN Audio A/S). All rights reserved. Jabra® is a trademark of GN Audio A/S. The Bluetooth® word mark and logos are registered trademarks owned by the Bluetooth SIG, Inc. and any use of such marks by GN Audio A/S is under license.

MADE IN CHINA MODEL: HSC018WA; END085W



1.	Welcome5
2.	Jabra Evolve 65 TE overview6 2.1 Stereo variant
	2.2 Mono variant
	2.3 Included accessories (stereo and mono)
3.	How to wear
	3.2 Adjust the headband
	3.3 Position the microphone
4.	How to charge the battery 11
	4.1 Sleep mode
5.	How to connect
	5.1 Connect to PC (using Jabra Link 390)
	5.2 Connect to mobile device (using Bluetooth)
	5.3 Connect to PC (using USB cable)
6.	How to use 16
	6.1 Everyday use
	6.2 Multiple call handling
	6.3 Busylight
	6.4 Using the travel pouch
7.	Software and firmware21
	7.1 Jabra Direct
	7.2 Update firmware

8.	Support	22
	8.1 FAQ	

8.2 How to care for your headset

### 1. Welcome

Thank you for using the Jabra Evolve 65 TE. We hope you will enjoy it!

#### Jabra Evolve 65 TE features

- Connects to PC via Jabra Link 390 bluetooth adapter or USB cable
- Connects to mobile devices via Bluetooth
- Integrated busylight
- Superior music and voice capabilities
- Hi-Fi Sound

# 2. Jabra Evolve 65 TE overview

#### 2.1 Stereo variant



#### 2.2 Mono variant



# 2.3 Included accessories (stereo and mono)







Travel pouch USB cable

e USB-

Jabra Link 390 USB-A Bluetooth adapter

## 3. How to wear



#### 3.1 Left or right wearing style

The Jabra Evolve 65 TE can be worn on the left or right by flipping the microphone to the other side (270° limit). To prevent damaging or breaking the microphone, do not rotate it more than 270°.



#### 3.2 Adjust the headband

Adjust the headband to find the most comfortable fit.




#### 3.3 Position the microphone

It is recommended to position the microphone close to your mouth (0.5 inches).



The microphone is bendable for personal preference.



# 4. How to charge the battery

The headset battery will charge when connected to a PC using a USB cable, or when using any USB charger supplied with your mobile device.

The headset can still be used for calls while charging using a USB cable connected to a PC.

It takes approx. 2 hours to charge the battery.



#### 4.1 Sleep mode

When the headset is powered on, but not being used, it will automatically enter sleep mode after 15 minutes to conserve battery. To manually exit sleep mode, press any button on the headset.

After 24 hours of sleep mode, the headset will power down completely. To power the headset back on, slide the **On/off/connect** switch from **On** to **Off**, and then back to **On**.

Sleep mode is enabled by default, and can be disabled using Jabra Direct.

### 5. How to connect

#### 5.1 Connect to PC (using Jabra Link 390)

- 1. Ensure the headset is switched on.
- Plug the Jabra Link 390 dongle into a USB port on your PC. The headset and Jabra Link 390 are already pre-connected.



# 5.2 Connect to mobile device (using Bluetooth)

- 1. Wear the headset.
- 2. Hold (3 secs) the **On/off/connect** switch in the connect position until you hear the voice guided instructions. The Bluetooth indicator will flash blue.
- 3. Follow the voice guided instructions to connect.



#### 5.3 Connect to PC (using USB cable)

- 1. Ensure the headset is switched on.
- 2. Plug the headset into a USB port on your PC using the supplied USB cable.



## 6. How to use



### 6.1 Everyday use

	Function	Action
	Headset on/off	Slide the <b>On/off/connect</b> switch
	Answer/end call	Tap the <b>Multi-function</b> button
-	Reject call	Double-tap the <b>Multi-</b> <b>function</b> button
	Battery and connection status	Tap the <b>Multi-function</b> button when not on a call
	Enable/disable Voice prompts	Press and hold the  Multi-function button while turning on the headset
	Adjust volume	Tap the <b>Volume up</b> or <b>Volume down</b> button
	Manual busylight on/off	Simultaneously tap the Volume up and Volume down buttons
	Enable/disable Busylight function	Simultaneously press and hold (3 secs) the <b>Volume up</b> and <b>Volume down</b> buttons
	Mute/unmute microphone	Press and hold (2 secs) the <b>Volume down</b> button

#### 6.2 Multiple call handling

The headset can accept and handle multiple calls at the same time.

Function	Action
End current call and answer incoming call	Tap the  Multi-function button
Switch between held call and active call*	Press and hold (2 secs) the <b>Multi-function</b> button
Put current call on hold and answer incoming call*	Press and hold (2 secs) the Multi-function button
Reject incoming call, when on a call	Double-tap the <b>Multi-function</b> button

<sup>\*</sup>Requires Microsoft Teams headset variant

#### 6.3 Busylight

The busylight indicator on the headset can be turned on to let others know that you are busy.

#### MANUALLY TURN BUSYLIGHT ON/OFF

To manually turn the busylight on/off, tap both the **Volume up** and **Volume down** buttons at the same time.


#### **ENABLE/DISABLE BUSYLIGHT FUNCTION**

To enable/disable the busylight function, press and hold (3 secs) both the **Volume up** and **Volume down** buttons at the same time.



#### 6.4 Using the travel pouch

When transporting the headset from location to location, it is recommended to use the travel pouch to prevent damaging the headset.



The earcups can only be rotated in one direction. To prevent breaking the headset, do not rotate the earcups in the opposite direction.

# 7. Software and firmware

#### 7.1 Jabra Direct

Jabra Direct is computer software designed to support, manage and enable optimal functionality for Jabra devices.

Download the latest free version from jabra.com/direct

#### 7.2 Update firmware

Firmware updates improve performance or add new functionality to Jabra devices.

- Connect the Jabra Evolve 65 TE to a computer.
- 2. Use Jabra Direct to check for the latest firmware updates.

## 8. Support

#### 8.1 FAQ

View the FAQs on jabra.com/support

#### 8.2 How to care for your headset

- Always store the headset with the power off and safely protected.
- Avoid storage at extreme temperatures (above 50°C/122°F or below -10°C/14°F). This can shorten battery life and may adversely affect the headset.